























































































































































































 0A Version number	 0B Factory default	 000600 PS2 keyboard mode
 000601 Serial port mode	 000602 USB keyboard mode	 000603 USB Serial port mode
 000604 RF mode	 0B006 Reset	 013300 Default mode
 013301 Single triggering scanning mode	 013302 triggering delay scanning mode	 013303 triggering forbid scanning mode
 013304 Automatic continuous scan mode	 013305 Automatic flashing scan Mode	 014200 Turn off sound
 0B142 Turn on sound	 00031 Turn on CapsLock	 00030 Turn off CapsLock
 00041 Enable send the digit through KeyPad	 00040 Disable send the digit through KeyPad	 01400 Turn off the ID code before the barcode
 01401 Turn on the ID before the barcode	 0005000 American	 0005001 Belgian
 0005002 Brazil	 0005003 Canada-Frech	 0005004 Croatia
 0005005 Czech Republic	 0005006 Slovakia	 0005007 Denmark
 0005008	 0005009	 0005010



























Finland  0005011 Hungary	France  0005012 Italy	Germany  0005013 Latin America
 0005014 Nether lands	 0005015 Norway	 0005016 Poland
 0005017 Portuga	 0005018 Yugos lavia/Serbia	 0005019 Slovenia
 0005020 Spanish	 0005021 Sweden	 0005022 Switzer land - French
 0005023 Switzer land- German	 0005024 England	 0005025 General
 0005026 Turkey -F	 0005027 Turkey-Q	 000701 600(Baud Rate)
 000702 1200(Baud Rate)	 000703 2400(Baud Rate)	 000704 4800(Baud Rate)
 000705 9600(Baud Rate)	 000706 19200(Baud Rate)	 000707 38400(Baud Rate)
 000708 57600(Baud Rate)	 000709 115200(Baud Rate)	 001200 NO Handshake Protocol
 001201 XON/OFF	 001202 RTS/CTS	 001203 ACK/NCK
 0013020	 0013050	 00081

Handshaking signal response time-2 seconds	Handshaking signal response time-5 seconds	8 bit
 00080 7 bit	 00090 1 bit	 00091 2 bit
 001000 No check	 001001 Odd check	 001002 Even check
 001003 Mark check	 001004 blank space	 0B010 Reset
 01261 Enable CODE 11	 01260 Disable CODE 11	 00221 Enable CODE 39
 00220 Disable CODE 39	 00231 Enable FULL ASCII	 00230 Disable FULL ASCII
 00261 Enable CODE 32	 00260 Disable CODE 32	
 00621 Enable CODE 93	 00620 Disable CODE 93	 00691 Enable CODE 128
 00690 Disable CODE 128	 00701 Enable CODE128 ISBT	 00700 Disable CODE128 ISBT
 00851 Enable CODABAR	 00850 Disable CODABAR	 00961 Enable Interleaved 2 of 5 Code
 00960 Disable Interleaved 2 of 5 Code	 01061 Enable Industrial 2 of 5 code	 01060 Disable Industrial 2 of 5 code

 01461 Enable Matrix 2 of 5 Code	 01460 Disable Matrix 2 of 5 Code	 01571 Enable China postal service code
 01570 Disable China postal service code	 01151 Enable MSI code	 01150 Disable MSI code
 00341 Enable UPC-A	 00340 Disable UPC-A	 00351 Enable UPC-E
 00350 Disable UPC-E	 00361 Enable EAN-13	 00360 Disable EAN-13
 00371 Enable EAN-8	 00370 Disable EAN-8	 0131m CODE11- set the ID code as "Z"
 0131Z CODE11- set the ID code as "Z"	 01321 CODE11-turn on Multiple authentication	 01320 CODE11-turn off Multiple authentication
 00241 CODE39-turn on the MOD43 authentication	 00240 CODE39-turn off the MOD43 authentication	 00251 CODE39- turn on the authentication
 00250 CODE39-- turn off the authentication	 002700 CODE39-without leading character	 002704 CODE39-set the leading character as "+"
 00281 CODE39-turn on the start/stop character	 00280 CODE39-turn on the start/stop character	 0031a CODE39- set the code ID as "a"
 0031Z CODE39- set the code ID as "Z"	 00331 CODE39-turn on Multiple authentication	 00330 CODE39- turn off Multiple authentication

 0066h CODE93- set the code ID as "h"	 0066Z CODE93- set the code ID as "Z"	 00681 CODE93- turn on Multiple authentication
 00680 CODE93 turn on Multiple authentication	 0081g CODE128- set the code ID as "g"	 0081Z CODE128- set the code ID as "Z"
 00841 CODE128-turn on Multiple authentication	 00840 CODE128-turn off Multiple authentication	 00861 CODABAR-turn on the start/stop character
 00860 CODABAR--turn on the start/stop character	 00901 CODABAR-Allow wide gap	 00900 CODABAR-forbid wide gap
 0094k CODABAR set the code ID as "k"	 0094Z CODABAR-set the code ID as "Z"	 00951 CODABAR-turn on Multiple authentication
 00950 CODABAR-turn off Multiple authentication	 0104i Interleaved 2 of 5 Code-set the code ID as "i"	 0104Z Interleaved 2 of 5 Code-set the code ID as "Z"
 01051 Interleaved 2 of 5 Code-turn on Multiple authentication	 01050 Interleaved 2 of 5 Code-turn off Multiple authentication	 0113j Industrial 2 of 5 code-set the code ID as "j"
 0113Z Industrial 2 of 5 code-set the code ID as "Z"	 01141 Industrial 2 of 5 code-turn On Multiple authentication	 01140 Industrial 2 of 5 code-turn off Multiple authentication
 0053f MSI-set the code ID as "f"	 0053Z MSI-set the code ID as "Z"	 01251 MSI-turn On Multiple authentication

 01250 MSI-turn off Multiple authentication	 00381 Enable UPC-E change into UPC-A	 00380 Disable UPC-E change into UPC-A
 00391 Enable UPC-A change into EAN-13	 00390 Disable UPC-A change into EAN-13	 00481 Enable EAN-13 change into ISBN
 00480 Disable EAN-13 change into ISBN	 01501 Enable EAN-13 change into ISSN	 01500 Disable EAN-13 change into ISSN
 0049b UPC-A-set the code ID as“b”	 0049Z UPC-A-set the code ID as“Z”	 0050c UPC-E-set the code ID as“c”
 0050Z UPC-E-set the code ID as“Z”	 0052d EAN-13-set the code ID as“e”	 0052Z EAN-13-set the code ID as“Z”
 00550 Close the Attached Code of UPC/EAN	 00551 Add Two Bit Attached Codes to UPC/EAN	 00552 Add Five Bit Attached Codes to UPC/EAN
 00553 Add Two Bit and Five Bit Attached Codes to UPC/EAN	 00541 UPC/EAN-turn On Multiple authentication	 00540 UPC/EAN--turn Off Multiple authentication
 0202011000\$0D Add the suffix --ENTER	 0202011000\$0A Add the suffix --SKIP	 0202011000\$0D\$0A Add the suffix – ENTER and SKIP
 0202011000\$09 Add the suffix--TAB	 0B20201 Remove the suffix	 0202002000\$02 Add “STX”in front of barcode
 0202003000\$03 Add the“ETX”behind the barcode	 020002080100000 Lower case	 020002090100000 upper case
 0B20002	 00461	 00460

Recover	EAN-13 Send Check Digit	EAN-13 Forbid Sending Check Digit
 00421 UPCA Send Check Digit	 00420 UPCA Forbid Sending Check Digit	 00400 UPCA Send Check Digit
 00401 UPCA Forbid Sending Check Digit	 00411 UPCE Send Check Digit	 00410 UPCE Forbid Sending Check Digit
 00431 UPCE Sending Check Digit	 00430 UPCE Forbid Sending Check Digit	 00441 EAN-13 Send the country code
 00440 EAN-13 Forbid Sending the country code	 00451 EAN-8 Send the country code	 00450 EAN-8 Forbid Sending the country code
 00471 EAN-8 send Check Digit	 00470 EAN-8 forbid sending Check Digit	 KeyMulOn Turn on the KeyMulOn
 KeyMulOff Turn off the KeyMulOn	 00000\$00 transfer speed -00(fastes)	 00000\$10 transfer speed -10 millisecond
 00000\$20 transfer speed -20 millisecond	 00000\$30 transfer speed -30 millisecond	 00000\$40 transfer speed -40 millisecond
 00000\$50 transfer speed -50 millisecond	 00000\$60 transfer speed -60 millisecond	 00000\$70 transfer speed -70 millisecond
 00000\$80 transfer speed -80 millisecond	 00000\$99 transfer speed -99 millisecond	